

Recommended RL by sensor ID

TGS2610-C00

Sensor ID #	RL(k Ω) with $\pm 1\%$ tolerance			
	5%LEL	10%LEL	15%LEL	20%LEL
# 05	1.57	1.05	0.82	0.70
# 06	1.73	1.16	0.91	0.77
# 07	1.90	1.27	1.00	0.84
# 08	2.09	1.40	1.10	0.93
# 09	2.31	1.54	1.21	1.02
# 10	2.54	1.70	1.33	1.13
# 11	2.79	1.87	1.47	1.24
# 12	3.07	2.05	1.61	1.36
# 13	3.38	2.26	1.78	1.50
# 14	3.72	2.49	1.96	1.65
# 15	4.10	2.74	2.15	1.82
# 16	4.51	3.02	2.37	2.00
# 17	4.97	3.32	2.61	2.20
# 18	5.47	3.65	2.87	2.43
# 19	6.02	4.02	3.16	2.67
# 20	6.62	4.43	3.48	2.94
# 21	7.29	4.87	3.83	3.24
# 22	8.02	5.36	4.21	3.56
# 23	8.83	5.90	4.64	3.92
# 24	9.72	6.50	5.11	4.32
# 25	10.7	7.15	5.62	4.75
# 26	11.8	7.87	6.19	5.23
# 27	13.0	8.66	6.81	5.75
# 28	14.3	9.53	7.49	6.33

TGS2611-C00

Sensor ID #	RL(k Ω) with $\pm 1\%$ tolerance			
	5%LEL	10%LEL	15%LEL	20%LEL
# 01	1.00	0.72	0.59	0.51
# 02	1.10	0.79	0.65	0.56
# 03	1.21	0.87	0.71	0.62
# 04	1.33	0.95	0.79	0.68
# 05	1.47	1.05	0.87	0.75
# 06	1.62	1.16	0.95	0.83
# 07	1.78	1.27	1.05	0.91
# 08	1.96	1.40	1.15	1.00
# 09	2.15	1.54	1.27	1.10
# 10	2.37	1.70	1.40	1.21
# 11	2.61	1.87	1.54	1.33
# 12	2.87	2.05	1.70	1.47
# 13	3.16	2.26	1.87	1.62
# 14	3.48	2.49	2.05	1.78
# 15	3.83	2.74	2.26	1.96
# 16	4.22	3.02	2.49	2.15
# 17	4.64	3.32	2.74	2.37
# 18	5.11	3.65	3.01	2.61
# 19	5.62	4.02	3.32	2.87
# 20	6.19	4.43	3.65	3.16
# 21	6.81	4.87	4.02	3.48
# 22	7.50	5.36	4.42	3.83
# 23	8.25	5.90	4.87	4.22
# 24	9.09	6.50	5.36	4.64